



Feature:

1. Used in conjunction with RH2816PT zone pager
2. Can page 8 RH2816PTs, up to 128 zones
3. With 16 zone paging buttons, audio signals are transmitted in a balanced manner
4. Using twisted pair as the transmission medium, the remote control distance can reach 1KM
5. Can cascade 5 remote control zones/paging microphones
6. Can adjust the paging volume
7. The function buttons are made of aluminum and light-touch soft keys to control the switch
8. With bell prompt and silent switch function
9. With full zone on/off control function, users can easily perform full zone paging broadcast
10. Function control: One volume adjustment, 8 device selection keys, 16 zone manual selection keys, One full-on, one full-key, one power switch, one address setting switch, one lock key, One microphone switch button, one LINE input port, one LINK output port, one audio source channel selection switch
11. Indicator light: Zone status indicator light CH1 ~ CH16, 8 device selection indicators, 1 microphone on status indicator light

Specification:

Microphone input	MIC:600 ohms (Ω) 5mV, unbalanced
Line output	LINE:10k ohms (Ω) 10V, balanced
Frequency response	MIC, LINE:60 Hz ~ 16k Hz (\pm 1 dB)
Non-linear distortion	THD<0.5% at 1kHz
Signal-to-noise ratio S/N	>70 dB
Number of controllable zones	16 zones "CH1 ~ CH16"
Number of controlled devices	8 DCI-10P
Maximum system configuration	5
Zone output control	You can manually select and activate any zone
Power supply (DC)	DC 24V
Power consumption	5~10W
Machine size	70(H) \times 238(W) \times 170(D) mm
Net weight	2.3Kg