



### Feature:

1. 20 MIC mono channels, 4 stereo inputs.
2. With 4 group outputs.
3. 4 AUX bus auxiliary outputs (including EFF).
4. 1 stereo return (assignable to main output or group output).
5. One set of monitor headphone outputs.
6. LPF low-pass filter output from stereo (60-150HZ adjustable).
7. Built-in 24 DSP digital effects.
8. Built-in USB player, MP3 playback, USB direct recording.
9. Built-in Bluetooth 5.0 receiving and playing.
10. USB audio sound card (connected to computer) transmits the sound played by the computer to the mixer.
11. Built-in 48V phantom power supply, each channel with independent switch.
12. Main output 9-band stereo graphic equalizer.
13. USB can be switched with one stereo, USB can be adjusted independently.
14. Mono channel 100HZ low-frequency attenuation switch (high-pass filter).
15. XLR input transistor dual differential microphone amplifier.
16. 3-band parametric equalization per channel, 80Hz.
17. Mono channel with (350Hz-3.5K mid-range sweep frequency). 12KHz.
18. MUTE switch for each input channel, PFL headphone switch.
19. Smooth 100MM travel fader.
20. 12-segment precise three-color LED level light to display signal status.
21. 12V (LAMP) DJ light XLR interface.
22. Applicable to global power supply voltage, power 30 watts, flexible to use.

### ► Specification:

Product size	750 x 500 x 190MM
Packing size (inner box)	820 x 575 x 258MM
Outer box size	835 x 590 x 278MM
Net weight	12.5KG
Gross weight	16.1KG
Maximum output level	18dB
S/N signal-to-noise ratio	≥83dB
Total harmonic distortion	≤0.02% @ 0dB 1KHz
Frequency response	20Hz ~ 20KHz±0.5dB
Channel crosstalk	< -75dB @ 1KHz
Input impedance	MIC:600Ω, LINE:10KΩ, output impedance:100Ω
Microphone	MIC input:-60dB, Line input:-40dB
Stereo input impedance	10KΩ
Channel gain adjustment	-30dB
Three-band equalization adjustment range	±15dB
HI	12K Hz 15dB ±3dB
MID	2.5KHz 15dB ±3dB
LOW	80Hz 15dB ±3dB
Power output power	30W
Power voltage	100V-240V/50Hz