

Dual module amplifier L2-AMP+



Feature:

- 1. High integration, mixer/DSP/amplifier 3 in 1.
- 2. Same size hanging design as line array speakers, flexible matching.
- 3. PC or iPad remote control, Bluetooth wireless music playback.
- 4. Compact and exquisite cabinet, 1:1 appearance size ratio with matching line array full-range speakers, can be hung and installed with full-range speakers.

Specification:

Amplifier output 4 channels	full-range 2x1500W@8, ultra-low 2x1500W@8
Frequency response	20Hz-20kHz ±0.5dB;
Rated voltage	100~240V AC 50~60Hz
Signal-to-noise ratio	Typical > 115dB(20Hz - 20kHz A-weighted @8Ω)
THD+N (0.1W-1/2Power)	< 0.08% (Typical < 0.05%
Sampling rate/quantization accuracy	48kHz / 24 Bit
Filter type	HPF/LPF/31 band GEQ/8 band PEQ/1k taps FIR filter
Input channels	4 Mic/Line in; 2 Line in; 2 AES inputs; 1 stereo Bluetooth input
Built-in effects	3 stereo effects Reverb/Delay/Chorus
Control method	Interface: TCP/IP, built-in WIFI Software: PC / iPad
Dimensions (W x H x D)	448 x 296 x 156 mm / 17.6 x 11.7 x 6.1 in
Weight	10.7 kg / 23.5 lbs