

High-Fidelity Performance-Grade Wireless Waist Pack Y9-YMSL1



► Feature:

1. Waist-pack wireless transmitter, can be paired with a lavalier microphone or a headset microphone, can be connected to international brand lavalier headset microphones
2. High contrast display: can display frequency, frequency number, group number, battery power, transmission signal strength, mute status and other information
3. Standard mini-XLR interface, strong compatibility, can be connected to different microphones
4. Equipped with 4 setting buttons, equipped with an easy-to-use navigation menu, easy to set and use
5. Transmitter parameters can be modified: support modifying the frequency, transmission Radiated power, volume, etc
6. Support multi-color LED indicator: 8 different color labels can be displayed to identify paired channels

► Specification:

Audio interface	Mini-XLR
Frequency range	610.05-695.35MHz
Dynamic range	105dB
Frequency response	20-20KHz
Frequency stability	±0.005%
Working distance	180m (open and interference-free)
Battery specifications	2×1.5V AA
Output power	high/medium/low three gears can be switched
Weight	75g (excluding battery and microphone)
Shell material	metal
Dimensions	66*23*88 mm (length*width*height, excluding antenna)
Battery life	high power about 7 hours; Medium power about 8 hours; Low power about 10 hours